

UltraVideo

2-Port DVI-D Splitter



Best Use of Technology for Our Earth

DVI-D Distribution Amplifier with Stereo Audio

Model: BDAS102



BDAS102 is a DVI-D distribution amplifier for DVI-D signals, it can accept a DVI-D signal from a computer and output to amplified signal to two display monitors.

Features

- ◆ Connects up to 2 DVI displays at the same time to one video source.
- ◆ Built in analog stereo audio.
- ◆ Supports high resolution
- ◆ PC: VGA, SVGA, XGA, SXGA, UXGA
- ◆ DVI cable to be used up to 15meters (output/input)
- ◆ Made in Taiwan

Specification

DVI Input : 1 (DVI-D 29 pin)
DVI Output : 2 (DVI-D 29 pin)
Audio Input : 1 PHONE JACK ϕ 3.5
Audio Output : 2 PHONE JACK ϕ 3.5
Supports Bandwidth : 27MHz~165MHz
Supports Resolution : PC: VGA, SVGA, XGA, SXGA, UXGA
Operation Temperature : -10°C~45°C
Storage Temperature : -30°C~70°C
Power Consumption : 500mA
Power Supply : DC5V 1AMP included
DIMENSIONS(WxHxD) : 145 x 95 x 37 mm

Connection Diagram



Taiwan Design and Plan (BENEVO Technology Co., Ltd.) Copyright©2012 BENEVO®
Service: 02-66177160 Website: www.benevo.com.tw Email: support@benevo.com.tw
BENEVO is a registered trademark, all other trademarks belong to the respective owners.